

USER MANUAL

NANLUX

INNOVATE · ILLUMINATE

TK-140B/TK-280B

DMX REFERENCE GUIDE

WWW.NANLUX.COM

CATALOG

CCT 8bit	01	PULSE	08
CCT 16bit	01	STORM	09
ULTIMATE DMX 8bit - CCT MODE	02	TV	10
ULTIMATE DMX 8bit - EFFECT MODE	03	PAPARAZZI	11
DMX EFFECT CHART		CANDLE/FIRE	12
CCT LOOP	05	BAD BULB	13
INT LOOP	06	FIREWORK	14
FLASH	07	EXPLOSION	15
		WELDING	16

CCT 8bit

CHANNEL	VALUE	%	FUNCTION	NOTES
1	0-255	0-100	Dimmer 0% to 100%	
2	0-255	0-100	CCT	2700K - 7500K

CCT 16bit

CHANNEL	VALUE	%	FUNCTION	NOTES
1-2	0-65535	0-100	DIMMER 0% to 100%	
3-4	0-65535	0-100	CCT	2700K - 7500K

ULTIMATE DMX 8bit - CCT MODE

CHANNEL	VALUE	%	FUNCTION	NOTES
1	0-255	0-100	DIMMER 0% to 100%	
2	0-63 64-127 128-255	0-25 26-50 51-100	MODE CCT EFFECT RESERVED	0 ≤ value ≤ 63
3	0-255	0-100	CCT	2700K - 7500K
4-10			N/A	

ULTIMATE DMX 8bit - EFFECT MODE

CHANNEL	VALUE	%	FUNCTION	NOTES
1	0-255	0-100	Dimmer 0% to 100%	
2	0-63 64-127 128-255	0-25 26-50 51-100	MODE CCT EFFECT RESERVED	64 ≤ value ≤ 127
3	0-18 19-36 37-54 55-72 73-91 92-109 110-127 128-145 146-163 164-182 183-200 201-218 219-255	0-7 8-14 15-21 22-28 29-35 36-42 43-50 51-57 58-64 65-71 72-78 79-85 86-100	EFFECT MODE CCT LOOP INT LOOP FLASH PULSE STORM TV PAPARAZZI CANDLE/FIRE BAD BULB FIREWORK EXPLOSION WELDING RESERVED	

ULTIMATE DMX 8bit - EFFECT MODE

CHANNEL	VALUE	%	FUNCTION	NOTES
4	0-255	0-100	DMX EFFECTS PARAMETER #1	See DMX Effects chart
5	0-255	0-100	DMX EFFECTS PARAMETER #2	See DMX Effects chart
6	0-255	0-100	DMX EFFECTS PARAMETER #3	See DMX Effects chart
7	0-255	0-100	DMX EFFECTS PARAMETER #4	See DMX Effects chart
8	0-255	0-100	DMX EFFECTS PARAMETER #5	See DMX Effects chart
9	0-255	0-100	DMX EFFECTS PARAMETER #6	See DMX Effects chart
10	0-255	0-100	DMX EFFECTS PARAMETER #7	See DMX Effects chart

DMX EFFECT CHART

EFFECT	CCT LOOP 0 ≤ value ≤ 18			
CH4/PARAMETER #1	CCT HIGH			
CH5/PARAMETER #2	CCT LOW			
CH6/PARAMETER #3	SPEED			
CH7/PARAMETER #4	CYCLE: ONE WAY = 0-85(0%-33%) CYCLE: TWO WAY = 86-170(34%-66%) CYCLE: REVERSE = 171-255(67%-100%)			
CH8/PARAMETER #5	ADD-ON: OFF = 0-63(0%-25%)	ADD-ON: FLASH = 64-127 (26%-50%)	ADD-ON: RANDOM FLASH = 128-191(51%-75%)	ADD-ON: PULSE = 192-255 (76%-100%)
CH9/PARAMETER #6	N/A	INTERVALS	SPEED	PULSES/MIN
CH10/PARAMETER #7	N/A	FLASH RATIO	N/A	N/A

DMX EFFECT CHART

EFFECT	INT LOOP 19 ≤ value ≤ 36			
CH4/PARAMETER #1	DIM LOW			
CH5/PARAMETER #2	CCT			
CH6/PARAMETER #3	SPEED			
CH7/PARAMETER #4	CYCLE: ONE WAY = 0-85(0%-33%) CYCLE: TWO WAY = 86-170(34%-66%) CYCLE: REVERSE = 171-255(67%-100%)			
CH8/PARAMETER #5	ADD-ON: OFF = 0-63(0%-25%)	ADD-ON: FLASH = 64-127 (26%-50%)	ADD-ON: RANDOM FLASH = 128-191(51%-75%)	ADD-ON: PULSE = 192-255 (76%-100%)
CH9/PARAMETER #6	N/A	INTERVALS	SPEED	PULSES/MIN
CH10/PARAMETER #7	N/A	FLASH RATIO	N/A	N/A

DMX EFFECT CHART

EFFECT	FLASH 37 ≤ value ≤ 54	
CH4/PARAMETER #1	CCT	
CH5/PARAMETER #2	INTERVALS	
CH6/PARAMETER #3	FLASH RATIO	
CH7/PARAMETER #4	PAUSE: OFF = 0-127(0%-50%)	PAUSE: ON = 128-255(51%-100%)
CH8/PARAMETER #5	N/A	
CH9/PARAMETER #6	N/A	
CH10/PARAMETER #7	N/A	

DMX EFFECT CHART

EFFECT	PULSE 55 ≤ value ≤ 72
CH4/PARAMETER #1	CCT
CH5/PARAMETER #2	PULSES/MIN
CH6/PARAMETER #3	N/A
CH7/PARAMETER #4	N/A
CH8/PARAMETER #5	N/A
CH9/PARAMETER #6	N/A
CH10/PARAMETER #7	N/A

DMX EFFECT CHART

EFFECT	STORM 73 ≤ value ≤ 91	
CH4/PARAMETER #1	CCT	
CH5/PARAMETER #2	FLASH TIMES HIGH	
CH6/PARAMETER #3	FLASH TIMES LOW	
CH7/PARAMETER #4	TRIGGER: AUTO = 0-127(0%-50%)	TRIGGER: MANUAL = 128-255(51%-100%)
CH8/PARAMETER #5	INTERVAL HIGH	Trigger: OFF = 0-127(0%-50%) Trigger: ON = 128-255(51%-100%)
CH9/PARAMETER #6	INTERVAL LOW	N/A
CH10/PARAMETER #7	PAUSE: OFF = 0-127(0%-50%) PAUSE: ON = 128-255(51%-100%)	N/A

DMX EFFECT CHART

EFFECT	TV 92 ≤ value ≤ 109
CH4/PARAMETER #1	DIM LOW
CH5/PARAMETER #2	CCT
CH6/PARAMETER #3	CCT SHIFT
CH7/PARAMETER #4	SPEED
CH8/PARAMETER #5	N/A
CH9/PARAMETER #6	N/A
CH10/PARAMETER #7	N/A

DMX EFFECT CHART

EFFECT	PAPARAZZI 110 ≤ value ≤ 127
CH4/PARAMETER #1	CCT
CH5/PARAMETER #2	SPEED
CH6/PARAMETER #3	N/A
CH7/PARAMETER #4	N/A
CH8/PARAMETER #5	N/A
CH9/PARAMETER #6	N/A
CH10/PARAMETER #7	N/A

DMX EFFECT CHART

EFFECT	CANDLE/FIRE 128 ≤ value ≤ 145
CH4/PARAMETER #1	DIM LOW
CH5/PARAMETER #2	CCT
CH6/PARAMETER #3	CCT SHIFT
CH7/PARAMETER #4	SPEED
CH8/PARAMETER #5	FLICKER: OFF = 0-127(0%-50%) FLICKER: ON = 128-255(51%-100%)
CH9/PARAMETER #6	N/A
CH10/PARAMETER #7	N/A

DMX EFFECT CHART

EFFECT	BAD BULB 146 ≤ value ≤ 163
CH4/PARAMETER #1	CCT
CH5/PARAMETER #2	INTENSITY
CH6/PARAMETER #3	SPEED
CH7/PARAMETER #4	N/A
CH8/PARAMETER #5	N/A
CH9/PARAMETER #6	N/A
CH10/PARAMETER #7	N/A

DMX EFFECT CHART

EFFECT	FIREWORK 164 ≤ value ≤ 182
CH4/PARAMETER #1	CCT
CH5/PARAMETER #2	CCT SHIFT
CH6/PARAMETER #3	SPEED
CH7/PARAMETER #4	DECAY
CH8/PARAMETER #5	N/A
CH9/PARAMETER #6	N/A
CH10/PARAMETER #7	N/A

DMX EFFECT CHART

EFFECT	EXPLOSION 183 ≤ value ≤ 200	
CH4/PARAMETER #1	CCT	
CH5/PARAMETER #2	DECAY	
CH6/PARAMETER #3	TRIGGER: AUTO = 0-127(0%-50%)	TRIGGER: MANUAL = 128-255(51%-100%)
CH7/PARAMETER #4	SPEED	Trigger: OFF = 0-127(0%-50%) Trigger: ON = 128-255(51%-100%)
CH8/PARAMETER #5	N/A	
CH9/PARAMETER #6	N/A	
CH10/PARAMETER #7	N/A	

DMX EFFECT CHART

EFFECT	WELDING 201 ≤ value ≤ 218
CH4/PARAMETER #1	DIM LOW
CH5/PARAMETER #2	CCT
CH6/PARAMETER #3	SPEED
CH7/PARAMETER #4	PAUSE: OFF = 0-127[0%-50%] PAUSE: ON = 128-255[51%-100%]
CH8/PARAMETER #5	N/A
CH9/PARAMETER #6	N/A
CH10/PARAMETER #7	N/A

Version: V1 2020-12-25

 +86-754-85751187

 +86-754-85300887

 info@nanlux.com

 Zhanglin,324,Dongli Chenghai Shantou Guangdong China

Guangdong NanGuang Photo&Video Systems Co., Ltd