

Cinelex TRX

All-In-One Wireless DMX Transmitter & Receiver

UNIVERSALLY COMPATIBLE

Full-size DMX connectors ensure seamless integration with any lighting rig.

DUAL-FUNCTION (TX/RX)

Switch between TX & RX modes – no need for dedicated units.

SIMPLE SETUP

Link to a LumenRadio transmitter or receiver with a single button-press.

V-MOUNT OR GOLD MOUNT

Use V-Mount (TRX-V) or Gold Mount (TRX-A) batteries, with simultaneous pass-through to power the light fixture.

PROFESSIONAL-READY

Robust design, constructed with extruded aluminium – built to withstand tough rental & on-set environments.



Wireless Protocol

Protocol	LumenRadio
Operational Frequency	2.4GHz (2402–2480MHz)
Range	Up to 100m (environment dependent)
DMX Standards	DMX512, DMX512 (1990) & DMX512-A
RDM	ANSI E1.20 (in Receive mode only)

Power

DC-in	5–30V
Power Consumption	1W

Controls

1x TX/RX Toggle Select	Switch Between 'Transmit' & 'Receive' Modes
1x "SYNC" Button	Synchronise TRX with Transmitter or Receiver

Connectors

1x DMX XLR 5-Pin Male	
1x DMX XLR 5-Pin Female	
1x Battery Plate Male & Female	V-Mount (TRX-V) or Gold Mount (TRX-A)
1x 2.1mm DC-In Power Socket	

Size (without Antennae)

Weight	370g
Dimensions	155mm x 90mm x 65mm (L x W x D)

W - www.cinelex.tv | E - info@cinelex.tv | T - +44 (0) 1784 450 506
Cinelex, Unit 10, Sky Business Park, Eversley Way, Egham, TW20 8RF, UK